19-2151; Rev 0; 8/01

MAXIM

Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface

General Description

The MAX5308/MAX5309 are 10-bit, eight channel, low-power, voltage-output, digital-to-analog converters (DACs) in a space-saving 16-pin TSSOP package. The wide +2.7V to +5.5V supply voltage range and less than 215µA (max) supply current per DAC are excellent for low-power and low-voltage applications. The low 2nV-s glitch energy of the MAX5308/MAX5309 makes them ideal for digital control of fast-response, closed-loop systems.

The MAX5308 has a digital output (DOUT) that can be used for daisy-chaining multiple devices. The MAX5309 has a hardware reset input ($\overline{CLR}$) which clears all registers and DACs to zero. The MAX5308/MAX5309 have a software shutdown feature that reduces the supply current to 1µA. The MAX5308/MAX5309 feature a load DAC ($\overline{LDAC}$) function that updates the output of all eight DACs simultaneously.

The 3-wire SPI™, QSPI™, MICROWIRE™ and DSP-compatible serial interface allows the input and DAC registers to be updated independently or simultaneously with a single software command. These devices use a double-buffered design to minimize the digital-noise feedthrough from the digital inputs to the outputs.

The MAX5308/MAX5309 operating temperature range is from -40°C to +85°C.

Applications

Gain and Offset Adjustment

Power Amplifier Control

Process Control I/O Boards

Portable Instrumentation Equipment

Control of Optical Components


Features

- **Eight Highly Integrated 10-Bit DACs in 16-Pin TSSOP (6.4mm × 5mm) Package**
- **Ultra-Low Glitch Energy <2nV-s**
- **Low Total Supply Current: 1.7mA (max) with $V_{REF} = V_{DD} = +5.5V$**
- **+2.7V to +5.5V Wide Single-Supply Range**
- **Fast 5µs Settling Time**
- **Software-Selectable Shutdown Mode < 1µA**
- **15MHz 3-Wire SPI, QSPI, and MICROWIRE-Compatible Serial Interface**
- **Power-Up Reset to Zero Scale**

Ordering Information

PART	TEMP. RANGE	PIN-PACKAGE
MAX5308EUE	-40°C to +85°C	16 TSSOP
MAX5309EUE	-40°C to +85°C	16 TSSOP

Pin Configuration



SPI and QSPI are trademarks of Motorola, Inc.

MICROWIRE is a trademark of National Semiconductor, Corp.

For pricing, delivery, and ordering information, please contact Maxim/Dallas Direct! at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface

ABSOLUTE MAXIMUM RATINGS

V_{DD} to GND ..... -0.3V to +6V
All Other Pins to GND .....-0.3V to (V_{DD} + 0.3V)
Continuous Power Dissipation (T_A = +70°C)
16-Pin TSSOP (derate 9.4mW/°C above +70°C) 775mW
Maximum Current into Any Pin .....±50mA
Operating Temperature Range .....-40°C to +85°C
Junction Temperature .....+150°C
Storage Temperature Range .....-65°C to +150°C
Lead Temperature (soldering, 10s) .....+300°C

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(V_{DD} = +2.7V to +5.5V, GND = 0, V_{REF} = V_{DD}, C_L = 200pF, R_L = 2kΩ, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at V_{DD} = +5V, T_A = +25°C.)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
STATIC ACCURACY (Notes 1, 2)						
Resolution	N		10			Bits
Integral Nonlinearity	INL			±0.5	±2	LSB
Differential Nonlinearity	DNL	Guaranteed monotonic			±0.5	LSB
Offset Error (Note 3)	V_{OE}			±10	±60	mV
Offset Error Temperature Coefficient				±10		µV/°C
Gain Error (Note 3)	V_{GE}			±0.1	±1	% of FS
Gain Error Temperature Coefficient				±5		ppm/°C
REFERENCE INPUT						
Reference Input Voltage Range (Note 4)	V_{REF}		0.8		V_{DD}	V
Reference Input Impedance	R_{REFIN}		135	200	265	kΩ
Reference Current	I_{REFPD}	In power-down mode		1	10	µA
DAC OUTPUTS						
Output Voltage Range		With no-load	0.020		V_{DD} - 0.020	V
DC Output Impedance				0.5		Ω
Capacitive Load	C_L			500		pF
Resistive Load	R_L			2		kΩ
Short-Circuit Current		V_{DD} = +5V		33		mA
		V_{DD} = +2.7V		20		
Wake-Up Time		From shutdown mode		24		µs

ELECTRICAL CHARACTERISTICS (continued)

(V_{DD} = +2.7V to +5.5V, GND = 0, V_{REF} = V_{DD}, C_L = 200pF, R_L = 2kΩ, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at V_{DD} = +5V, T_A = +25°C.)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
DIGITAL INPUTS (SCLK, DIN, $\overline{CS}$, $\overline{LDAC}$, $\overline{CLR}$—MAX5309)						
Input High Voltage	V_{IH}	V_{DD} = +5V ±10%	2.4			V
		V_{DD} = +3V ±10%	2.1			
Input Low Voltage	V_{IL}	V_{DD} = +5V ±10%			0.8	V
		V_{DD} = +3V ±10%			0.6	
Input Leakage Current	I_{IN}	All digital inputs 0 or V_{DD}		±0.1	±10	µA
Input Capacitance	C_{IN}			10		pF
DIGITAL OUTPUT (MAX5308)						
Output Low Voltage	V_{OL}	I_{SINK} = 1mA			0.5	V
Output High Voltage	V_{OH}	I_{SOURCE} = 1mA	V_{DD} - 0.5			V
DYNAMIC PERFORMANCE						
Voltage-Output Slew Rate	SR	Positive and negative		1		V/µs
Voltage-Output Settling Time	t_S	FFHhex to 2FFhex		5		µs
Digital Feedthrough		Code 0, all digital inputs from 0 to V_{DD}		0.5		nV-s
DAC Glitch Impulse		Major carry glitch		2		nV-s
DAC Output Noise				600		$µV_{p-p}$
DAC to DAC crosstalk				0.5		nV-s
POWER REQUIREMENTS						
Supply Voltage Range	V_{DD}		2.7		5.5	V
Supply Current with No-Load (Note 5)	I_{DD}	All digital inputs at 0 or V_{DD}, V_{DD} = V_{REF} = +5.5V		1.5	1.7	mA
		All digital inputs at 0 or V_{DD}, V_{DD} = +5.5V, V_{REF} = +1.2V		1.1	1.3	
		All digital inputs at 0 or V_{DD}, V_{DD} = V_{REF} = +3V		1.3		
		Shutdown mode		1	10	µA

Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface

ELECTRICAL CHARACTERISTICS (continued)

(V_{DD} = +2.7V to +5.5V, GND = 0, V_{REF} = V_{DD}, C_L = 200pF, R_L = 2kΩ, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at V_{DD} = +5V, T_A = +25°C.)


PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
TIMING CHARACTERISTICS						
Serial Clock Frequency	f_{SCLK}		0		15	MHz
SCLK Pulse Width High	t_{CH}		33			ns
SCLK Pulse Width Low	t_{CL}		33			ns
$\overline{CS}$ Fall to SCLK Fall Setup Time	t_{CSS}		16			ns
SCLK Fall to $\overline{CS}$ Rise Setup Time	t_{CSH}		20			ns
$\overline{LDAC}$ Pulse Width Low	$t_{LDACPWL}$		20			ns
$\overline{CLR}$ Pulse Width Low	t_{CLRPWL}	MAX5309 only	20			ns
DIN to SCLK Fall Setup Time	t_{DS}		16			ns
DIN to SCLK Fall Hold Time	t_{DH}		10			ns
$\overline{CS}$ Pulse Width High	t_{CSPWH}		20			ns
SCLK Rise to DOUT Fall	t_{SDL}	Load capacitance = 20pF			50	ns
SCLK Rise to DOUT Rise	t_{SDH}	Load capacitance = 20pF			50	ns

Note 1: Static accuracy tested without load.
Note 2: Linearity is tested within codes 1Dhex to 3E3hex.
Note 3: Gain and offset tested within codes 1Dhex to 3E3hex.
Note 4: Static accuracy specifications valid for V_{REF} = 1.2V to V_{DD}.
Note 5: Current scales linearly between these two extremes of V_{REF}.


Typical Operating Characteristics

(V_{DD} = +5V, T_A = +25°C, unless otherwise noted.)


INTEGRAL NONLINEARITY vs. DIGITAL INPUT CODE




DIFFERENTIAL NONLINEARITY vs. DIGITAL INPUT CODE




REFERENCE VOLTAGE INPUT FREQUENCY RESPONSE




SUPPLY CURRENT vs. TEMPERATURE




SUPPLY CURRENT vs. REFERENCE VOLTAGE




SUPPLY CURRENT vs. SUPPLY VOLTAGE




SUPPLY CURRENT vs. SUPPLY VOLTAGE (CODE = 3FFHEX)



SOURCE-AND-SINK CURRENT CAPABILITY



FULL-SCALE ERROR vs. REFERENCE VOLTAGE




Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface


Typical Operating Characteristics (continued)

(V_{DD} = +5V, T_A = +25°C, unless otherwise noted.)


FULL-SCALE ERROR vs. LOAD CURRENT




REFERENCE FEEDTHROUGH AT 1kHz, R_L = 2kΩ, C_L = 200pF



DAC-TO-DAC CROSSTALK




DYNAMIC RESPONSE




V_{REF} = +2.5V, R_L = 2kΩ, C_L = 200pF
SWITCHING FROM CODE 000HEX TO FFFHEX

MAJOR-CARRY TRANSITION




V_{REF} = +2.5V, R_L = 2kΩ, C_L = 200pF

DIGITAL FEEDTHROUGH (SCLK = 1.4MHz)




V_{REF} = +2.5V, R_L = 2kΩ, C_L = 200pF
CS = +5V, DIN = 0
DAC 1 CODE SET to 800HEX

NEGATIVE FULL-SCALE SETTLING TIME



POSITIVE FULL-SCALE SETTLING TIME



Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface

Pin Description

PIN	NAME	FUNCTION
1	SCLK	Serial Clock Input. Serial data is loaded on the falling edge of SCLK.
2	DIN	Serial Data Input
3	$\overline{LDAC}$	Load DAC. $\overline{LDAC}$ is an asynchronous active-low input that updates the DAC outputs simultaneously. If $\overline{LDAC}$ is driven low, the DAC registers are transparent.
4	REF	Reference Voltage Input
5–12	OUT_	Analog Output Signal
13	GND	Ground
14	V_{DD}	Power Supply. Bypass V_{DD} to GND with a 0.1µF capacitor.
15	DOUT	Data Output (MAX5308). DOUT is updated on the falling edge of SCLK.
	$\overline{CLR}$	Asynchronous Clear DAC (MAX5309). Active-low input to clear all DACs and registers. Resets all outputs to zero.
16	$\overline{CS}$	Chip-Select Input (active-low)

Detailed Description

The MAX5308/MAX5309 are 10-bit, eight-channel, low-power, voltage-output digital-to-analog converters (DACs) that are easily addressed using a simple 3-wire serial interface. These devices feature eight double-buffered DACs using a common 16-bit serial to parallel shift register, a power-on reset (POR) circuit and eight output buffer amplifiers.

Figure 1 shows the block diagram of MAX5308/MAX5309 . The shift register converts a serial 16-bit word to parallel data for each input register operating with a clock rate of up to 15MHz. The 3-wire digital interface to the shift register consists of chip-select ($\overline{CS}$), serial clock (SCLK), and data input (DIN). Serial data at DIN is loaded on the falling edge of SCLK.

The eight double-buffered DACs consist of input and DAC registers. The input registers are directly connected to the shift register and hold the result of the most recent write operation. The eight 10-bit DAC registers hold the current output code for the respective DAC. Data can be transferred from the input registers to the DAC registers by either the hardware interface (LDAC) or by software command. The output of DACs are buffered through eight Rail-to-Rail® op amps.

The MAX5308 has a digital output (DOUT) which can be used to daisy chain multiple devices on a single serial bus. The MAX5309 contains a hardware shutdown ($\overline{CLR}$) to clear all internal registers and power-down all DACs.

The MAX5308/MAX5309 require an external reference such as the MAX6161 family. The reference voltage range is from 0.8V to V_{DD}.

POR circuitry gives the DACs a defined state during start-up. At power-on, the DAC outputs reset to zero through a 100kΩ resistor, providing additional safety for applications that drive valves or other transducers that need to be off at power-up.

The MAX5308/MAX5309 feature low digital feedthrough and minimize glitch energy on MSB transitions. The 3-wire SPI, QSPI, MICROWIRE and DSP-compatible serial interface saves additional circuit board space

Serial Interface Configuration

The MAX5308/MAX5309 3-wire serial interface are compatible with MICROWIRE, SPI, QSPI, and DSPs (Figure 2 and Figure 3). The chip-select input ($\overline{CS}$) frames the serial data loading at DIN. Following $\overline{CS}$'s high-to-low transition, the data is shifted synchronously and latched into the input register on each falling edge of the serial clock input (SCLK). Each serial word is 16 bits, the first four bits are the control word followed by 10 data bits (MSB first) as shown in Table 1. The last two data bits must be zeros. The 10-bit DAC code is unipolar binary with 1LSB = V_{REF} /1024.

The serial input register transfers its contents to the input registers after loading 16 bits of data and driving $\overline{CS}$ high. $\overline{CS}$ must be brought high for a minimum of

Rail-to-Rail is a registered trademark of Nippon Motorola, Ltd.

Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface

Table 1. Serial Interface Configuration

16-BIT SERIAL WORD																	
CONTROL BITS				DATA BITS													
MSB															LSB		
C3	C2	C1	C0	D09	D08	D07	D06	D05	D04	D03	D02	D01	D00			DESC.	FUNCTION
0	0	0	0	X	X	X	X	X	X	X	X	X	X	0	0	NOP	No Operation
0	0	0	1	X	X	X	X	X	X	X	X	X	X	0	0	RESET	RESET All Internal Registers. Power-down DACs, outputs pulled down with 100kΩ. Equivalent to software $\overline{CLR}$.
0	0	1	0											0	0	DAC 1	D9–D0 to Input Register 1, DAC Output Unchanged
0	0	1	1											0	0	DAC 2	D9–D0 to Input Register 2, DAC Output Unchanged
0	1	0	0											0	0	DAC 3	D9–D0 to Input Register 3, DAC Output Unchanged
0	1	0	1											0	0	DAC 4	D9–D0 to Input Register 4, DAC Output Unchanged
0	1	1	0											0	0	DAC 5	D9–D0 to Input Register 5, DAC Output Unchanged
0	1	1	1											0	0	DAC 6	D9–D0 to Input Register 6, DAC Output Unchanged
1	0	0	0											0	0	DAC 7	D9–D0 to Input Register 7, DAC Output Unchanged
1	0	0	1											0	0	DAC 8	D9–D0 to Input Register 8, DAC Output Unchanged
1	0	1	0											0	0	DAC 1–4	D9–D0 to Input Registers 1–4 and DAC Registers 1–4, DAC Outputs Updated (Write-Thru).
1	0	1	1											0	0	DAC 5–8	D9–D0 to Input Registers and DAC Registers, DAC Outputs Updated (Write-Thru).
1	1	0	0											0	0	DAC 1–8	D9–D0 to Input Registers and DAC Registers, DAC Outputs Updated (Write-Thru).
1	1	0	1											0	0	DAC 1–8	D9–D0 to Input Registers, DAC Outputs Unchanged
1	1	1	0	DAC 8	DAC 7	DAC 6	DAC 5	DAC 4	DAC 3	DAC 2	DAC 1	X	X	0	0	DAC 1–8	Input Registers to DAC Registers Indicated by Ones, DAC Outputs Updated, Equivalent to Software $\overline{LDAC}$. (No effect on DACs indicated by 0s.)

X = Don't Care




Figure 1. Functional Diagram

20ns before the next write sequence since a write sequence is initiated on a falling edge of $\overline{CS}$. If $\overline{CS}$ goes high prior to completing 16 cycles of SCLK, the input data is discarded. To initiate a new data transfer, drive $\overline{CS}$ low again. The serial clock (SCLK) can be either high or low between $\overline{CS}$ write pulses. Figure 4 shows the timing diagram for the complete 3-wire serial interface transmission.

The MAX5308/MAX5309 digital inputs are double-buffered. Depending on the command issued through the serial interface, the input register(s) can be loaded without affecting the DAC register(s), the DAC register(s) can be loaded directly, or all eight registers can be updated simultaneously from the input registers.

Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface

Table 2. Serial Interface Power-Up and Shutdown Commands

CONTROL BITS				DATA BITS													
C3	C2	C1	C0	DAC 8	DAC 7	DAC 6	DAC 5	DAC 4	DAC 3	DAC 2	DAC 1	D03	D02	D01	D00	DESC.	FUNCTION
1	1	1	1									1	1	X	X	Power-Up	Power-Up individual DAC buffers indicated by data in DAC1 through DAC8. A one indicates the DAC output is connected and active. A zero does not affect the DACs present state.
1	1	1	1									0	1	X	X	Shut-down 1	Shutdown individual DAC buffers indicated by data in DAC1 through DAC8. A one indicates the DAC output is high-impedance. A zero does not affect the DACs' present state.
1	1	1	1									1	0	X	X	Shut-down 2	Shutdown individual DAC buffers indicated by data in DAC1 through DAC8. A one indicates the DAC is shutdown and the output is connected to GND through a 1kΩ resistor. A zero does not affect the DACs present state.
1	1	1	1									0	0	X	X	Shut-down 3	Shutdown individual DAC buffers indicated by data in DAC1 through DAC8. A one indicates the DAC is shutdown and the output is connected to GND through a 100kΩ resistor. A zero does not affect the DACs present state.

X = Don't Care

Shutdown Modes

The MAX5308/MAX5309 include three software-controlled shutdown modes that reduce the supply current to less than 1µA. In two of the three shutdown modes (shutdown 2 and 3) the outputs are independently connected to ground through a 1kΩ or 100kΩ (default) resistor. The third shutdown (shutdown 1) command leaves the DACs outputs high impedance. Table 2 lists the three shutdown modes of operation as well as the power-up command.

Serial-Data Output (DOUT)

The DOUT (MAX5308) follows DIN with a 16 clock cycle delay. The DOUT is capable of driving 20pF load with a 50ns (max) delay from the falling edge of SCLK.

DOUT is primarily used for daisy-chaining multiple devices. Optionally, DOUT can be used to monitor the serial interface for valid communications by connecting DOUT to a microprocessor input.

Hardware Clear ($\overline{CLR}$)

The MAX5309 has an active-low $\overline{CLR}$ input. Drive $\overline{CLR}$ low to clear all internal registers, shutdown all DACs,




Figure 2. Connections for MICROWIRE




Figure 3. Connections for SPI/QSPI

and terminate all DAC outputs to GND through 100kΩ resistors. $\overline{CLR}$ is asynchronous and can be applied at any time. If $\overline{CLR}$ is toggled low during loading of a serial word, that word will terminate and must be reloaded.

Reference Input

The external reference input has a typical input impedance of 200kΩ. The input voltage range is from 800mV to V_{DD}. V_{DD} can be used as the reference for the MAX5308/MAX5309. The DAC outputs are then ratiometric to V_{DD}.

Output Buffer

The rail-to-rail buffer amplifier is stable with any combination of resistive loads greater than 2kΩ and capacitive loads less than 500pF. With a capacitive load of 200pF the output buffers have a slew rate of 1V/µs. For a 1/4 FS to 3/4 FS output transition, the amplifier output typically settles to 1/2 LSB in less than 10µs when loaded with 2kΩ in parallel with 200pF.

Power-On Reset

The MAX5308/MAX5309 have a POR circuit to set the DACs' output to zero when V_{DD} is first applied. This ensures that unwanted DAC output voltages will not occur immediately following a system startup, such as after a loss of power. Upon initial power-up the POR circuit ensures that all DAC registers are cleared, the DACs are powered-down, and their outputs are terminated to GND through a 100kΩ resistor.

Applications Information

Daisy-Chaining Devices

Any number of MAX5308s can be daisy-chained by connecting the DOUT pin of one device to the DIN pin of the following device in the chain (Figure 5). To write to the chain, drive $\overline{CS}$ low until all n × 16 clock cycles (where n is the number of devices in the chain) and associated data have been applied to the first device. When $\overline{CS}$ is driven high, each device in the chain acts on the 16 bits in its input register. To adjust a single device in the chain, a No-Operation (NOP) command must be loaded for all other devices.

Figure 6 shows an alternate method of connecting several MAX5308s or MAX5309s. In this configuration, the data bus is common to all devices; data is not shifted through a daisy chain. More I/O lines are required in this configuration because a dedicated chip-select input ($\overline{CS}$) is required for each IC.

Unipolar Output

The MAX5308/MAX5309 are normally configured for unipolar output. Table 3 lists the unipolar output voltages vs. digital codes.

Bipolar Output

The MAX5308/MAX5309 outputs can be configured for bipolar operation using Figure 7's circuit.

$$V_{OUT} = V_{REF} [(2D / 1024) - 1]$$

Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface




Figure 4. Timing Diagram

where D is the decimal value of the DACs' binary input code. Table 4 shows digital codes (offset binary) and corresponding output voltages for the Figure 7 circuit.

Power-Supply Considerations

On power-up, all input and DAC registers are cleared and DOUT is low.

Bypass V_{DD} to GND with a 4.7µF capacitor in parallel with a 0.1µF capacitor. Use short lead lengths and place the bypass capacitors as close to the supply pins as possible.

Table 3. Unipolar Code Table

DAC CONTENTS MSB		LSB	ANALOG OUTPUT
1111	1111	11	$+V_{REF}\left(\frac{1023}{1024}\right)$
1000	0000	01	$+V_{REF}\left(\frac{513}{1024}\right)$
1000	0000	00	$+V_{REF}\left(\frac{512}{1024}\right)=\frac{+V_{REF}}{2}$
0111	1111	11	$+V_{REF}\left(\frac{511}{1024}\right)$
0000	0000	01	$_{REF}\left(\frac{1}{1024}\right)$
0000	0000	00	0V

Table 4. Bipolar Code Table

DAC CONTENTS MSB		LSB	ANALOG OUTPUT
1111	1111	11	$+V_{REF}\left(\frac{511}{512}\right)$
1000	0000	01	$+V_{REF}\left(\frac{1}{512}\right)$
1000	0000	00	0V
0111	1111	11	$-V_{REF}\left(\frac{1}{512}\right)$
0000	0000	01	$-V_{REF}\left(\frac{511}{512}\right)$
0000	0000	00	$-V_{REF}\left(\frac{512}{512}\right)=-V_{REF}$




Figure 5. Daisy-Chaining MAX5308s





Figure 6. Multiple MAX5308s or MAX5309s Sharing a Common DIN Line

Low-Power, Low-Glitch, Octal 10-Bit Voltage-Output DACs with Serial Interface

Simplified Block Diagram






Figure 7. Bipolar Output Circuit


Chip Information

TRANSISTOR COUNT: 19,000

PROCESS TECHNOLOGY: BiCMOS

Package Information

TSSOP,NO PADS.EPS



SYMBOL	COMMON DIMENSIONS			
	MILLIMETERS		INCHES	
	MIN.	MAX.	MIN.	MAX.
A	———	1.10		.043
A_1	0.05	0.15	.002	.006
A_2	0.85	0.95	.033	.037
b	0.19	0.30	.007	.012
b1	0.19	0.25	.007	.010
c	0.090	0.20	.0035	.008
c1	0.090	0.135	.0035	.0053
D	SEE VARIATIONS		SEE VARIATIONS	
E	4.30	4.50	.169	.177
e	0.65 BSC		.026 BSC	
H	6.25	6.50	.246	.256
L	0.50	0.70	.020	.028
N	SEE VARIATIONS		SEE VARIATIONS	
α	0°	8°	0°	8°

JEDEC			VARIATIONS			
MO-153	N		MILLIMETERS		INCHES	
			MIN.	MAX.	MIN.	MAX.
AB-1	14	D	4.90	5.10	.193	.201
AB	16	D	4.90	5.10	.193	.201
AC	20	D	6.40	6.60	.252	.260
AD	24	D	7.70	7.90	.303	.311
AE	28	D	9.60	9.80	.378	.386

NOTES:
1. DIMENSIONS D AND E DO NOT INCLUDE FLASH
2. MOLD FLASH OR PROTRUSIONS NOT TO EXCEED 0.15mm PER SIDE
3. CONTROLLING DIMENSION: MILLIMETER
4. MEETS JEDEC OUTLINE MO-153. SEE JEDEC VARIATIONS TABLE.
5. "N" REFERS TO NUMBER OF LEADS
6. THE LEAD TIPS MUST LIE WITHIN A SPECIFIED ZONE. THIS TOLERANCE ZONE IS DEFINED BY TWO PARALLEL PLANES. ONE PLANE IS THE SEATING PLANE, DATUM [-C-]; THE OTHER PLANE IS AT THE SPECIFIED DISTANCE FROM [-C-] IN THE DIRECTION INDICATED.

MAXIM
PROPRIETARY INFORMATION

TITLE: PACKAGE OUTLINE, TSSOP, 4.40 MM BODY

APPROVAL	DOCUMENT CONTROL NO.	REV	
	21-0066	E	1/1

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

© 2001 Maxim Integrated Products Printed USA MAXIM is a registered trademark of Maxim Integrated Products.

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А