maxim integrated™

MAX9918/MAX9919/MAX9920

-20V to +75V Input Range, Precision Uni-/Bidirectional, Current-Sense Amplifiers

General Description

The MAX9918/MAX9919/MAX9920 are single-supply, high-accuracy current-sense amplifiers with a high input common-mode range that extends from -20V to +75V. These amplifiers are well suited for current monitoring of inductive loads such as motors and solenoids, where common-mode voltages can become negative due to inductive kickback, reverse-battery conditions, or transient events.

The MAX9918/MAX9920 feature adjustable gain set by an external resistive-divider network. The MAX9919 features fixed gains of 45V/V (MAX9919F) and 90V/V (MAX9919N). The MAX9918/MAX9919/MAX9920 operate as unidirectional amplifiers when V_{REFIN} = GND and as bidirectional amplifiers when V_{REFIN} = V_{CC}/2. The MAX9920 attenuates the input signal by a factor of 4 at the input level-shifting stage allowing the device to sense voltages up to 200mV (unidirectional operation) or ±100mV (bidirectional operation).

The MAX9918/MAX9919/MAX9920 operate with a single 5V supply voltage, are fully specified over the -40°C to +125°C automotive temperature range, and are available in an 8-pin SOIC package.

Applications

H-Bridge Motor Current Sensing

Solenoid Current Sensing

Current Monitoring of Inductive Loads

High- and Low-Side Precision Current Sensing

4x4 Transmission Control

Electronic Throttle Control

Super-Capacitor Charge/Discharge Monitoring in Hybrid Cars

Precision High-Voltage Current Monitoring

Features

- **-20V to +75V Input Common-Mode Voltage Range**
- **400µV (max) Input Offset Voltage**
- **0.6% (max) Gain Accuracy Error**
- **Uni- or Bidirectional Current Sensing**
- **Reference Input for Bidirectional OUT**
- **120kHz, -3dB Bandwidth (MAX9919N)**
- **Single-Supply Operation (4.5V to 5.5V)**
- **1mA Supply Current**
- **0.5µA (typ) Shutdown Current**
- **Rail-to-Rail Output**
- **-40°C to +125°C Automotive Temperature Range**

Ordering Information/ Selector Guide

PART	V_{SENSE} (mV)	GAIN (V/V)	PIN-PACKAGE
MAX9918ASA+	±50	Adjustable	8 SO-EP*
MAX9918ASA/V+	±50	Adjustable	8 SO-EP*
MAX9919FASA+	±50	45	8 SO-EP*
MAX9919FASA/V+	±50	45	8 SO-EP*
MAX9919NASA+	±50	90	8 SO-EP*
MAX9919NASA/V+	±50	90	8 SO-EP*
MAX9920ASA+	±200	Adjustable	8 SO-EP*
MAX9920ASA/V+	±200	Adjustable	8 SO-EP*


Note: *All devices operate over the -40°C to +125°C temperature range.*

+Denotes a lead(Pb)-free/RoHS-compliant package.

/V denotes an automotive qualified part.

**EP = Exposed pad.*

Typical Operating Circuit



For pricing, delivery, and ordering information, please contact Maxim Direct at 1-888-629-4642, or visit Maxim's website at www.maximintegrated.com.

19-5015; Rev 5; 1/13

ABSOLUTE MAXIMUM RATINGS

V_{CC} to GND .....-0.3V to +6V
RS+, RS- to GND (V_{CC} = 5V) .....-30V to +80V
RS+, RS- to GND (V_{CC} = 0V) .....-15V to +80V (15 minutes)
Differential Input Voltage (V_{RS+} - V_{RS-})
(MAX9918/MAX9919).....±15V (Continuous)
Differential Input Voltage
(V_{RS+} - V_{RS-}) (MAX9920) .....±5V (Continuous)
REFIN, FB, OUT to GND.....-0.3V to (V_{CC} + 0.3V)
SHDN to GND.....-0.3V to +20V
Output Short Circuit to V_{CC} or GND.....Continuous
Continuous Current into Any Pin
(Not to exceed package power dissipation) .....±20mA
Continuous Power Dissipation (T_A = +70°C)
8-Pin SO-EP (derate 24.4mW/°C above +70°C).....1951.2mW**
Junction Temperature.....+150°C
Storage Temperature Range .....-65°C to +150°C
Lead Temperature (soldering, 10s) .....+300°C
Soldering Temperature (reflow) .....+260°C

***As per JEDEC51 Standard (multilayer board).*

PACKAGE THERMAL CHARACTERISTICS (Note 1)

SO-EP
Junction-to-Ambient Thermal Resistance (θ_{JA}) .....41°C/W

Note 1: Package thermal resistances were obtained using the method described in JEDEC specification JESD51-7, using a four-layer board. For detailed information on package thermal considerations, refer to **www.maximintegrated.com/thermal-tutorial**.

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(V_{CC} = 5V, V_{RS+} = V_{RS-} = +14V, V_{SENSE} = (V_{RS+} - V_{RS-}) = 0V, V_{SHDN} = V_{GND} = 0V, V_{REFIN} = V_{CC}/2, R_L = 100kΩ; for MAX9918, A_V = 90V/V, R2/R1 = 89kΩ/1kΩ; for MAX9920, A_V = 20V/V, R2/R1 = 79kΩ/1kΩ; T_A = -40°C to +125°C, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS			MIN	TYP	MAX	UNITS
Input Offset Voltage (Note 2)	V_{OS}	MAX9918	V_{RS+} = V_{RS-} = +14V, V_{REFIN} = 0V	T_A = +25°C		±0.14	±0.4	mV
				T_A = -40°C to +125°C			±0.7	
			V_{RS+} = V_{RS-} = -2V, V_{REFIN} = 0V	T_A = +25°C		±0.08	±0.4	
				T_A = -40°C to +125°C			±1.3	
		MAX9919_	V_{RS+} = V_{RS-} = +14V, V_{REFIN} = 0V	T_A = +25°C		±0.18	±0.4	
				T_A = -40°C to +125°C			±0.9	
			V_{RS+} = V_{RS-} = -2V, V_{REFIN} = 0V	T_A = +25°C		±0.11	±0.4	
				T_A = -40°C to +125°C			±1.0	
		MAX9920	V_{RS+} = V_{RS-} = +14V, V_{REFIN} = 0V	T_A = +25°C		±0.48	±1.2	
				T_A = -40°C to +125°C			±3.0	
			V_{RS+} = V_{RS-} = -2V, V_{REFIN} = 0V	T_A = +25°C		±0.10	±0.9	
				T_A = -40°C to +125°C			±3.5	

ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = 5V, V_{RS+} = V_{RS-} = +14V, V_{SENSE} = (V_{RS+} - V_{RS-}) = 0V, V_{SHDN} = V_{GND} = 0V, V_{REFIN} = V_{CC}/2, R_L = 100kΩ; for MAX9918, A_V = 90V/V, R2/R1 = 89kΩ/1kΩ; for MAX9920, A_V = 20V/V, R2/R1 = 79kΩ/1kΩ; T_A = -40°C to +125°C, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETERS	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Input Offset Voltage Drift (Note 3)	V_{OSD}	MAX9918	V_{RS+} = V_{RS-} = +14V		±1.2		µV/°C
			V_{RS+} = V_{RS-} = -2V		±3.3		
		MAX9919_	V_{RS+} = V_{RS-} = +14V		±1.8		
			V_{RS+} = V_{RS-} = -2V		±1.8		
		MAX9920	V_{RS+} = V_{RS-} = +14V		±2.4		
			V_{RS+} = V_{RS-} = -2V		±8.8		
Common-Mode Range	V_{CM}	Inferred from CMRR tests		-20		+75	V
Common-Mode Rejection Ratio (Note 3)	CMRR	MAX9918, MAX9919	-2V ≤ V_{CM} ≤ +14V	80			dB
			-20V ≤ V_{CM} ≤ +75V	96			
		MAX9920	-2V ≤ V_{CM} ≤ +14V	72			
			-20V ≤ V_{CM} ≤ +75V	86			
Input Bias Current	I_{RS+}, I_{RS-}	-20V ≤ V_{CM} ≤ +75V	T_A = +25°C			±175	µA
			T_A = -40°C to +125°C			±250	
Input Offset Current	(I_{RS+} - I_{RS-})				0	±8	µA
Input Leakage Current in Shutdown		-20V ≤ V_{CM} ≤ +75V, V_{SHDN} = V_{CC} = 5V				±30	µA
Input Leakage Current		V_{RS+} = V_{RS-} = +14V, +75V, V_{CC} = 0V				±30	µA
Input Resistance		MAX9918, MAX9919_	Common mode		300		kΩ
			Differential		715		Ω
		MAX9920	Common mode		330		kΩ
			Differential		224		Ω
Full-Scale Sense Voltage (Note 4)	V_{SENSE}	Inferred from gain error test	MAX9918, MAX9919_		50		mV
			MAX9920		200		
Gain (Notes 2, 4)	G	MAX9918, MAX9920			Adj		V/V
		MAX9919F			45		
		MAX9919N			90		
Minimum Adjustable Gain	G_{ADJ}	MAX9918			30		V/V
		MAX9920			7.5		

ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = 5V, V_{RS+} = V_{RS-} = +14V, V_{SENSE} = (V_{RS+} - V_{RS-}) = 0V, V_{SHDN} = V_{GND} = 0V, V_{REFIN} = V_{CC}/2, R_L = 100kΩ; for MAX9918, A_V = 90V/V, R2/R1 = 89kΩ/1kΩ; for MAX9920, A_V = 20V/V, R2/R1 = 79kΩ/1kΩ; T_A = -40°C to +125°C, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS			MIN	TYP	MAX	UNITS
Gain Error (Note 2)	GE	MAX9918	V_{RS+} = V_{RS-} = +14V	T_A = +25°C, V_{REFIN} = 0V		±0.08	±0.6	%
				T_A = -40°C to +125°C, V_{REFIN} = 0V			±1.2	
			V_{RS+} = V_{RS-} = -2V, V_{REFIN} = 0V	T_A = +25°C		±0.02	±0.6	
				T_A = -40°C to +125°C			±1.0	
		MAX9919F	V_{RS+} = V_{RS-} = +14V, V_{REFIN} = 0V	T_A = +25°C		±0.13	±0.45	
				T_A = -40°C to +125°C			±1.2	
			V_{RS+} = V_{RS-} = -2V, V_{REFIN} = 0V	T_A = +25°C		±0.10	±0.45	
				T_A = -40°C to +125°C			±0.9	
		MAX9919N	V_{RS+} = V_{RS-} = +14V, V_{REFIN} = 0V	T_A = +25°C		±0.16	±0.6	
				T_A = -40°C to +125°C			±1.2	
			V_{RS+} = V_{RS-} = -2V, V_{REFIN} = 0V	T_A = +25°C		±0.11	±0.6	
				T_A = -40°C to +125°C			±1.0	
		MAX9920	V_{RS+} = V_{RS-} = +14V, V_{REFIN} = 0V	T_A = +25°C		±0.29	±1.0	
				T_A = -40°C to +125°C			±1.7	
			V_{RS+} = V_{RS-} = -2V, V_{REFIN} = 0V	T_A = +25°C		±0.24	±1.0	
				T_A = -40°C to +125°C			±1.7	
FB Input Bias Current	I_{FB}	MAX9918, MAX9920				5	15	nA
Output-Voltage High (Note 4)	V_{CC} - V_{OH}	V_{SENSE} = 200mV for MAX9918, MAX9919_, V_{SENSE} = 400mV for MAX9920		R_L = 100kΩ to GND		3	10	mV
				R_L = 10kΩ to GND		12	40	
Output-Voltage Low (Note 4)	V_{OL}	V_{SENSE} = -200mV for MAX9918, MAX9919_, V_{SENSE} = -400mV for MAX9920		R_L = 100kΩ to V_{CC}		3	10	mV
				R_L = 10kΩ to V_{CC}		10	40	
Short-Circuit Current	I_{SC}	OUT shorted to V_{CC}				44		mA
		OUT shorted to GND				41		
Output Resistance	R_{OUT}					0.1		Ω
REFIN Voltage Range		Inferred from REFIN CMRR test		MAX9918, MAX9919_	0	V_{CC} /2	V_{CC} - 1.9	V
				MAX9920	0	V_{CC} /2	V_{CC} - 2.4	

ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = 5V, V_{RS+} = V_{RS-} = +14V, V_{SENSE} = (V_{RS+} - V_{RS-}) = 0V, V_{SHDN} = V_{GND} = 0V, V_{REFIN} = V_{CC}/2, R_L = 100kΩ; for MAX9918, A_V = 90V/V, R2/R1 = 89kΩ/1kΩ; for MAX9920, A_V = 20V/V, R2/R1 = 79kΩ/1kΩ; T_A = -40°C to +125°C, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETERS	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
REFIN Common-Mode Rejection Ratio	$REFIN_{CMRR}$	MAX9918, MAX9919_	0V ≤ V_{REFIN} ≤ (V_{CC} - 1.9V)	82	103		dB
		MAX9920	0V ≤ V_{REFIN} ≤ (V_{CC} - 2.4V)	75	90		
REFIN Current	I_{REFIN}	MAX9918, MAX9919_, V_{RS+} = V_{RS-} = ±50mV				±100	µA
		MAX9920, V_{RS+} = V_{RS-} = ±200mV				±100	
SHDN Logic-High	V_{IH}			2.0			V
SHDN Logic-Low	V_{IL}					0.8	V
SHDN Logic Input Current		0 ≤ V_{SHDN} ≤ V_{CC}				5	µA
Supply Voltage Range	V_{CC}	Inferred from PSRR test		4.5		5.5	V
Power-Supply Rejection Ratio (Note 3)	PSRR	MAX9918, MAX9919_	4.5V ≤ V_{CC} ≤ 5.5V	74	103		dB
		MAX9920	4.5V ≤ V_{CC} ≤ 5.5V	68	100		
Supply Current	I_{CC}	V_{RS+} = V_{RS-} = +14V	T_A = +25°C		0.7	1.2	mA
			T_A = -40°C to +125°C			1.5	
		V_{RS+} = V_{RS-} = -2V	T_A = +25°C		1.0	1.6	
			T_A = -40°C to +125°C			2.2	
Shutdown Supply Current	I_{CC_SHDN}	V_{SHDN} = V_{CC} = 5V			0.5	10	µA
Small Signal -3dB Bandwidth	BW	MAX9918, V_{SENSE} = 50mV			75		kHz
		MAX9919F, V_{SENSE} = 50mV			250		
		MAX9919N, V_{SENSE} = 50mV			120		
		MAX9920, V_{SENSE} = 200mV			230		
Slew Rate	SR	MAX9918			0.6		V/µs
		MAX9919F			0.9		
		MAX9919N			3.0		
		MAX9920			1.5		
1% Settling Time from V_{SENSE} Step		MAX9918	V_{SENSE} = 5mV to 50mV step		12		µs
			V_{SENSE} = 50mV to 5mV step		7		
		MAX9919F	V_{SENSE} = 5mV to 50mV step		3.5		
			V_{SENSE} = 50mV to 5mV step		2.5		
		MAX9919N	V_{SENSE} = 5mV to 50mV step		3.5		
			V_{SENSE} = 50mV to 5mV step		3		
		MAX9920	V_{SENSE} = 20mV to 200mV step		5		
			V_{SENSE} = 200mV to 20mV step		3		

ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = 5V, V_{RS+} = V_{RS-} = +14V, V_{SENSE} = (V_{RS+} - V_{RS-}) = 0V, V_{SHDN} = V_{GND} = 0V, V_{REFIN} = V_{CC}/2, R_L = 100kΩ; for MAX9918, A_V = 90V/V, R2/R1 = 89kΩ/1kΩ; for MAX9920, A_V = 20V/V, R2/R1 = 79kΩ/1kΩ; T_A = -40°C to +125°C, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETERS	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
1% Settling Time from V_{CM} Step		MAX9918, V_{SENSE} = 50mV	V_{CM} = -2V to +14V step		2.5		µs
			V_{CM} = +14V to -2V step		0.5		
		MAX9919F, V_{SENSE} = 50mV	V_{CM} = -2V to +14V step		2.5		
			V_{CM} = +14V to -2V step		0.5		
		MAX9919N, V_{SENSE} = 50mV	V_{CM} = -2V to +14V step		3.5		
			V_{CM} = +14V to -2V step		3.5		
		MAX9920, V_{SENSE} = 200mV	V_{CM} = -2V to +14V step		0.25		
			V_{CM} = +14V to -2V step		2.5		
Power-Up Time		MAX9918, V_{SENSE} = 50mV, 1% settling			4.5		µs
		MAX9919F, V_{SENSE} = 50mV, 1% settling			5		
		MAX9919N, V_{SENSE} = 50mV, 1% settling			6		
		MAX9920, V_{SENSE} = 200mV, 1% settling			5		
Max Capacitive Load Stability		No sustained oscillations (Note 5)		50			pF
Input-Referred Noise Voltage Density	e_n	10kHz	MAX9918, MAX9919_		60		nV/√Hz
			MAX9920		174		

Note 1: All devices are 100% production tested at T_A = +25°C. All temperature limits are guaranteed by design.

Note 2: V_{OS} is extrapolated from two point gain error tests. Measurements are made at V_{SENSE} = 5mV and 50mV for MAX9918/MAX9919N/MAX9919F, and V_{SENSE} = 20mV and 200mV for MAX9920.

Note 3: Extrapolated V_{OS} as described above in Note 2 is used to calculate V_{OS} drift, CMRR, and PSRR.


Note 4: OUT should be 100mV away from either rail to achieve rated accuracy, or limited by a V_{SENSE} of 50mV for the MAX9918/MAX9919N/MAX9919F and 200mV for the MAX9920.

Note 5: Not production tested. Guaranteed by design.


Typical Operating Characteristics

(V_{CC} = 5V, T_A = +25°C, unless otherwise noted.)


V_{OS} (V_{RS+} = +14V)




V_{OS} DRIFT (V_{RS+} = +14V)




V_{OS} (V_{RS+} = -2V)




V_{OS} DRIFT (V_{RS+} = -2V)




V_{OS} vs. V_{CM}




V_{OS} vs. V_{CC}




GAIN ERROR (V_{RS+} = +14V, MAX9919F, A_V = +45V/V)



GAIN ERROR (V_{RS+} = +14V, MAX9919N, A_V = +90V/V)




GAIN ERROR (V_{RS+} = -2V, MAX9919F, A_V = +45V/V)




Typical Operating Characteristics (continued)

(V_{CC} = 5V, T_A = +25°C, unless otherwise noted.)


GAIN ERROR
(V_{RS+} = -2V, MAX9919N, A_V = +90V/V)




GAIN ERROR vs. V_{CM}




GAIN ERROR vs. V_{CC}




LINEARITY vs. V_{SENSE}



LINEARITY vs. V_{SENSE}




LINEARITY vs. V_{SENSE}




Typical Operating Characteristics (continued)

(V_{CC} = 5V, T_A = +25°C, unless otherwise noted.)


LINEARITY vs. V_{SENSE}




LINEARITY vs. V_{SENSE}




LINEARITY vs. V_{SENSE}




V_{OUT} - V_{REFIN} vs. V_{SENSE}



V_{OUT} - V_{REFIN} vs. V_{SENSE}




V_{OH}/V_{OL} vs. I_{OH}




Typical Operating Characteristics (continued)

(V_{CC} = 5V, T_A = +25°C, unless otherwise noted.)


ICC vs. VCC




ICC vs.VCM




IBIAS vs. VCM




INPUT LEAKAGE CURRENT vs. VCM




DIFFERENTIAL RIN vs. VCM




GAIN vs. FREQUENCY




GAIN vs. FREQUENCY



GAIN vs. FREQUENCY




PSRR vs. FREQUENCY




Typical Operating Characteristics (continued)

(V_{CC} = 5V, T_A = +25°C, unless otherwise noted.)


SMALL-SIGNAL TRANSIENT (GAIN = 45V/V)




SMALL-SIGNAL TRANSIENT (GAIN = 90V/V)




LARGE-SIGNAL TRANSIENT (GAIN = 45V/V)




LARGE-SIGNAL TRANSIENT (GAIN = 90V/V)



COMMON-MODE STEP RESPONSE




OUTPUT RESPONSE TO COMMON-MODE TRANSIENT




Typical Operating Characteristics (continued)

(V_{CC} = 5V, T_A = +25°C, unless otherwise noted.)


SHUTDOWN ON/OFF DELAY




POWER-UP TIME




OUTPUT OVERDRIVE RECOVERY (30V/V)



OUTPUT OVERDRIVE RECOVERY (90V/V)



Pin Configuration



8 SO-EP

*EXPOSED PAD. CONNECT EP TO SOLID GROUND FOR PROPER THERMAL AND ELECTRICAL PERFORMANCE.

Pin Description

PIN	NAME	FUNCTION
1	RS+	Positive Current-Sensing Input. Power side connects to external sense resistor.
2	RS-	Negative Current-Sensing Input. Load side connects to external sense resistor.
3	SHDN	Active-High Shutdown Input. Connect to GND for normal operation.
4	GND	Ground
5	OUT	Current-Sense Output. V_{OUT} is proportional to V_{SENSE}.
6	FB	Feedback Input. Connect FB to a resistive-divider network to set the gain for the MAX9918 and MAX9920. See the *Adjustable Gain (MAX9918/MAX9920)* section for more information. Leave FB unconnected for the MAX9919 for proper operation.
7	REFIN	Reference Input. Set REFIN to $V_{CC}/2$ for bidirectional operation. Set REFIN to GND for unidirectional operation.
8	V_{CC}	5V Supply Voltage Input. Bypass V_{CC} to GND with 0.1µF capacitor.
—	EP	Exposed Pad. Connect to a large-area contiguous ground plane for improved power dissipation. Do not use as the only ground connection for the part.

Detailed Description

The MAX9918/MAX9919/MAX9920 are single-supply, high-accuracy uni-/bidirectional current-sense amplifiers with a high common-mode input range that extends from -20V to +75V. The MAX9918/MAX9919/MAX9920's input stage utilizes a pair of level shifters allowing a wide common-mode operating range when measuring the voltage drop (V_{SENSE}) across the current-sense resistor. The first level shifter accommodates the upper common-mode operating range from +2V to +75V. When the common-mode voltage falls below +2V, the second level shifter is used to accommodate negative voltages down to -20V.

The level shifters translate V_{SENSE} to an internal reference voltage where it is then amplified with an instrumentation amplifier. The instrumentation amplifier configuration provides high precision with input offset voltages of 400µV (max). Indirect feedback of the instrumentation amplifier allows the gain to be adjusted with an external resistive-divider network on the MAX9918/MAX9920. The MAX9919 is a fixed gain device available with laser-trimmed resistors for gains of 45V/V (MAX9919F) and 90V/V (MAX9919N).

The MAX9918/MAX9919 operate with a full-scale sense voltage of 50mV. The input stage of the MAX9920 provides an attenuation factor of 4, enabling a full-scale sense voltage of 200mV.

Uni-/Bidirectional Operation

The MAX9918/MAX9919/MAX9920 support both unidirectional and bidirectional operation. The devices operate in unidirectional mode with V_{REFIN} = V_{GND}. The output is then referenced to ground and the output voltage V_{OUT} is proportional to the positive voltage drop (V_{SENSE}) from RS+ to RS- (Figure 1).

The MAX9918/MAX9919 operate in bidirectional mode by application of a low-source impedance reference voltage in the 0V to V_{CC} - 1.9V range, (typically V_{CC}/2), to REFIN. For the MAX9920, the reference voltage range is 0V to V_{CC} - 2.4V (typically V_{CC}/2). The output voltage V_{OUT} relative to V_{REFIN} is then proportional to the ±V_{SENSE} voltage drop from RS+ to RS- (Figure 2).




Figure 1. Unidirectional Operation




Figure 2. Bidirectional Operation

Shutdown Mode

Drive SHDN high to enter low-power shutdown mode. In shutdown mode, the MAX9918/MAX9919/MAX9920 draw 0.5µA (typ) of quiescent current.

Adjustable Gain (MAX9918/MAX9920)

The MAX9918/MAX9920 feature externally adjustable gain set by a resistive-divider network circuit using resistors R1 and R2 (see the *Functional Diagram*). The gain frequency compensation is set for a minimum gain of 30V/V for the MAX9918 and 7.5V/V for the MAX9920. The gain G for the MAX9918/MAX9920 is given by the following equation:

$$G = \left(1 + \frac{R2}{R1}\right) \text{ (for MAX9918)}$$

and

$$G = \left(\frac{\left(1 + \frac{R2}{R1}\right)}{4}\right) \text{ (for MAX9920)}$$

Applications Information

Component Selection

Ideally, the maximum load current develops the full-scale sense voltage across the current-sense resistor. Choose the gain needed to yield the maximum output voltage required for the application:

$$V_{OUT} = V_{SENSE} \times G$$

where V_{SENSE} is the full-scale sense voltage, 50mV for the MAX9918/MAX9919, or 200mV for the MAX9920 and G is the gain of the device. G is externally adjustable for the MAX9918/MAX9920. The MAX9919 has a fixed gain version of 45V/V (MAX9919F) or 90V/V (MAX9919N).

In unidirectional applications (V_{REFIN} = 0V), select the gain of the MAX9918/MAX9920 to utilize the full output range between GND and V_{CC}. In bidirectional applications ($V_{REFIN} = V_{CC}/2$), select the gain to allow an output voltage range of $\pm V_{CC}/2$. V_{OUT} must be at least 100mV from either rail to achieve the rated gain accuracy.

Sense Resistor, R_{SENSE}

Choose R_{SENSE} based on the following criteria:

Accuracy: A high R_{SENSE} value allows lower currents to be measured more accurately. This is because offsets become less significant when the sense voltage is larger. In the linear region (100mV < V_{OUT} < V_{CC} - 100mV), there are two components to accuracy: input offset voltage (V_{OS}) and gain error (GE). Use the linear equation to calculate total error:

$$V_{OUT} = (G \pm GE) \times (V_{SENSE} \pm V_{OS})$$

For best performance, select R_{SENSE} to provide approximately 50mV (MAX9918/MAX9919) or 200mV (MAX9920) of sense voltage for the full-scale current in each application. Sense resistors of 5mΩ to 100mΩ are available with 1% accuracy or better.

Efficiency and Power Dissipation


At high current levels, the I^2R losses in R_{SENSE} can be significant. Take this into consideration when choosing the resistor value and its power dissipation (wattage) rating. Also, the sense resistor's value might drift if it is allowed to heat up excessively. The precision V_{OS} of the MAX9918/MAX9919/MAX9920 allows the use of small sense resistors to reduce power dissipation and reduce hot spots.

Inductance: Keep inductance low if I_{SENSE} has a large high-frequency component by using resistors with low inductance value.

Power-Supply Bypassing and Grounding

Bypass the MAX9918/MAX9919/MAX9920's V_{CC} to ground with a 0.1µF capacitor. Grounding these devices requires no special precautions; follow the same cautionary steps that apply to the rest of the system. High-current systems can experience large voltage drops across a ground plane, and this drop may add to or subtract from V_{OUT}. Using a differential measurement between OUT and REFIN prevents this problem. For highest current-measurement accuracy, use a single-point star ground. Connect the exposed pad to a solid ground to ensure optimal thermal performance.

Functional Diagram



Chip Information

PROCESS: BiCMOS

Package Information

For the latest package outline information and land patterns (footprints), go to **www.maximintegrated.com/packages**. Note that a "+", "#", or "-" in the package code indicates RoHS status only. Package drawings may show a different suffix character, but the drawing pertains to the package regardless of RoHS status.

PACKAGE TYPE	PACKAGE CODE	OUTLINE NO.	LAND PATTERN NO.
8 SO-EP	S8E+14	21-0111	90-0151

Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	10/09	Initial release	—
1	1/10	Updated *Functional Diagram*	16
2	12/10	Added automotive qualified part	1
3	6/11	Added MAX9920ASA/V+ to data sheet	1
4	7/11	Added automotive qualified parts for the MAX9919NASA/V+ and the MAX9920ASA/V+	1
5	1/13	Added automotive qualified part for the MAX9919FASA/V+	1

Maxim Integrated cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim Integrated product. No circuit patent licenses are implied. Maxim Integrated reserves the right to change the circuitry and specifications without notice at any time. The parametric values (min and max limits) shown in the Electrical Characteristics table are guaranteed. Other parametric values quoted in this data sheet are provided for guidance.

© 2013 Maxim Integrated Products, Inc. Maxim Integrated and the Maxim Integrated logo are trademarks of Maxim Integrated Products, Inc.

ООО «НИОКРсистемс» - это оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов. Реализуемая нашей компанией продукция насчитывает более полумиллиона наименований.

Благодаря этому наша компания предлагает к поставке практически не ограниченный ассортимент компонентов как оптовыми, мелкооптовыми партиями, так и в розницу.

Благодаря развитой сети поставщиков, помогаем в поиске и приобретении экзотичных или снятых с производства компонентов.

Наша компания это:

- Гарантия качества поставляемой продукции
- Широкий ассортимент
- Минимальные сроки поставок
- Техническая поддержка
- Подбор комплектации
- Индивидуальный подход
- Гибкое ценообразование
- Работаем по 275 ФЗ

ООО «НИОКР СИТЕМС»
Москва, 125362, Россия, ул. Вишневая, д. 9, к. 1, Блок 104 а и 104 в

Телефон: 8 (495) 268-14-82
Email: n@nsistems.ru

ИНН: 7735154786
ОГРН: 1167746717709