



Strip-crimp applicator for side feeding terminals

MKS-SC



Crimping applicator for end-feeding terminals


MK-L



Semi-automatic press

Semi-automatic crimping machines (presses) contact a wire to a chain terminal each time a footswitch is pressed.


AP-K2N



- Dimensions: (W×L×H)280×480×505mm
- Weight: Approx. 90kg(198lb)
- Power source: 100V AC, Single-phase 50/60Hz
- Pressure output: 14.7kN[1,500kg(3307lb)]
- Dies: Applicator replacement

Crimping applicator for side-feeding terminals

MKS-L




Crimping applicator for end-feeding flag terminals

MKF-L



Compact crimping applicator for side-feeding terminals

MKS-LS



Terminals and parts model number in alphabetical order	Hand tools for chain terminals	Hand tools for loose piece terminals					Hand tools for loose piece terminals		Extraction and Insertion tools	
									Extraction tool	Insertion tool
	YRS series  Dimensions: (W×L) 59×224mm	**YC series**  Dimensions: (W×L) 70×296mm	**YRM series**  Dimensions: (W×L) 59×224mm	**YRF series**  Dimensions: (W×L) 70×295mm 80×305mm	**YRK series**  Dimensions: (W×L×D) 75×314×25mm	**YRK-EX series**  Dimensions: (W×L×D) 75×314×25mm			 Extraction tool is used to extract contacts improperly inserted in the housing.	 Insertion tool allows contacts be inserted in the housing. This tool greatly increases efficiency especially when thin wires are used.
	YRS series	YC series	YRM series	YRF series	YRK · YRK-EX series		WC & JUC series JUK's Hand Tools	Terminal in loose form model No.		
JK-SP/SS2* **	YRS-370	–	–	–	–		–	–	KEJ-0.7 for plug, KEJ-0.4 for socket	–
J-SP/SS1* **	YRS-440	YC-440	–	–	–		–	J-BP/BS1***	DEJ-0.3	–
J-SP/SS2* **	YRS-330	–	–	–	–		–	–	DEJ-0.3	–
LFO-1.0-250N	–	–	–	–	–		JUCS-FO	–	–	–
LFO-2.5-250N	–	–	–	–	–		JUCS-FO	–	–	–
MD-SP12**	YRS-470	–	–	–	–		–	–	MEJ-06	–
MD-SP22**	YRS-460	–	–	–	–		–	–	MEJ-06	–
RA-SC1290	YRS-231	–	YRM-232 YRM-233	–	–		–	RA-BC12**	EJ-RA	–
RF-SC22**	–	–	YRM-230	–	–		–	RF-BC22**	–	–
RPJ-SP/SS2331	YRS-331	–	–	–	–		–	–	EJ-RPJ	–
SAA-21(T)-**	–	YC-141	–	–	–		–	LAA-21(T-)**	–	–
SAA-50(T)-**	–	YC-182	–	–	–		–	LAA-50(T)-**	–	–
SAA-51(T)-**	–	YC-142	–	–	–		–	LAA-51(T)-**	–	–
SAB-51(T)-**	–	YC-142	–	–	–		–	LAB-51(T)-**	–	–
SACH-003G-P0.2	YRS-1190	–	–	–	–		–	–	–	–
SACH-002GU-P0.3	YRS-858	–	–	–	–		–	–	–	–
SAN-002T-0.8A **SAN-002T-0.8K**	YRS-220	–	–	–	–		–	–	EJ-PH	–
SBH-001T-P0.5	–	YC-670R	–	–	–		WC-670	BBH-001T-P0.5	–	–
SBHL-002T-P0.5	YRS-857	–	–	–	–		–	–	–	–
SBHM-001T-P0.5	–	YC-670R	–	–	–		–	BBHM-001T-P0.5	EJ-BHMR	–
SBHS-002T-P0.5A	YRS-852	–	–	–	–		–	–	EJ-BHS2	–
SBHS-002T-P0.5A	–	–	–	–	–		–	–	EJ-BHS2	–
SBHSM-002T-P0.5	YRS-854	–	–	–	–		–	–	EJ-BHSW	–
SBHT-002T-P0.5	YRS-856 YRS-857	–	–	–	–		–	–	EJ-BHT	–
SBN-001T-1.0	YRS-170	YC-170R	–	–	–		–	BBN-001T-1.0	–	–
SCN-001T-1.0K **SCN-001T-P1.0**	YRS-191	YC-191R	–	–	–		WC-191	BCN-001T-1.0K BCN-001T-P1.0	–	–
SCS-41T-2.3	–	–	–	–	–		–	–	CSJ-23	–
SCSN-41T-P2.3	–	–	–	–	–		–	–	EJ-CSN	–
SCZH-002T-P0.5	YRS-492	–	–	–	–		–	–	–	–

Crimping tools

It is the manual tool that is convenience to terminate very small quantity of contacts for prototype or maintenance.
It is composed of two crimping dies for the conductor and insulation, and can be crimp easily.
YRK and YRK-EX can be used for mass-production.

Note: (1) These tools are for prototype tooling or repair.
(2) YC tool has two crimping sections (A and B). YRS tool has also two crimping sections by inverting upper dies.
Be sure to check applicable wires before use. Since the dies are fixed, the crimping height cannot be adjusted. Therefore, some of the applicable wires described in this catalog may not be crimped properly.
Before use, check for proper crimping (such as tensile strength, terminal/contact deformation).
(3) These tools are not applicable to 2-wire crimping.
(4) When hand crimping board-in terminals (SAN, SCN, SDN, SGN, SIN, SJN, SZN), care should be taken not to contaminate the solder tails of the terminals, as with greasy or oily fingers. If a solder problem arises, some cleaning of the tips of the terminal is advisable.
(5) WC and JUC hand tools are provided by J.S.T.(U.K.) LTD. and contact them about the details of these hand tools.

Note: Contact JST for wire range.

Crimping tools

Terminals and parts model number in alphabetical order	Hand tools						Hand tools		Extraction and Insertion tools	
	for chain terminals	for loose piece terminals					for loose piece terminals		Extraction tool	Insertion tool
	YRS series	YC series	YRM series	YRF series	YRK · YRK-EX series		WC & JUC series JUK's Hand Tools	Terminal in loose form model No.		
SDF-01T-1.0A	–	YC-045	–	–	–		–	LDF-01T-1.0A	–	–
SDF-01T-1.3AS	–	YC-045	–	–	–		–	LDF-01T-1.3AS	–	–
SDN-21T-P1.5	–	YC-600R	–	–	–		–	BDN-21T-P1.5	–	–
SDY-01T-P1.6ASV	–	YC-525R	–	–	–		–	BDY-01T-P1.6ASV	SLJ-1.4	–
SEH-001T-P0.6	YRS-260	YC-260R	–	–	–		WC-260	BEH-001T-P0.6	EJ-PH	–
SEH-001T-P0.6L	–	–	–	–	–		–	–	EJ-PH	–
SEH-002T-P0.6L	–	–	–	–	–		–	–	EJ-PH	–
SEH-003T-P0.6L	–	–	–	–	–		–	–	EJ-PH	–
SF1F-002(*)-P0.6	–	–	–	–	YRK-1220		–	–	EJ-JFAJ1100	–
SF1M-002(*)-M0.6A	–	–	–	–	YRK-1220		–	–	EJ-JFAJ1100	–
SF1F-21(*)-P0.6	–	–	–	–	YRK-1210		–	–	EJ-JFAJ1100	–
SF1M-21(*)-M0.6A	–	–	–	–	YRK-1210		–	–	EJ-JFAJ1100	–
SF3F-002(*)-P2.0	–	–	–	YRF-882	YRK-8821		–	BF3F-002(*)-P2.0	EJ-JFAJ3	–
SF3F-01(*)-P2.0	–	–	–	YRF-881	YRK-8811		–	BF3F-01(*)-P2.0	EJ-JFAJ3	–
SF3M-01(*)-M2.0N	–	–	–	YRF-881	YRK-8811		–	BF3M-01(*)-M2.0N	EJ-JFAJ3	–
SF3F-41(*)-P2.0	–	–	–	YRF-880	YRK-8801		–	LF3F-41(*)-P2.0	EJ-JFAJ3	–
SF3M-41(*)-M2.0N	–	–	–	YRF-880	YRK-8801		–	LF3M-41(*)-M2.0N	EJ-JFAJ3	–
SF3F-71(*)-P2.0	–	–	–	YRF-1070	YRK-1071		–	BF3F-71(*)-P2.0	EJ-JFAJ3	–
SF3M-71(*)-M2.0N	–	–	–	YRF-1071	YRK-1071		–	BF3M-71(*)-M2.0N	EJ-JFAJ3	–
SFO-41(T)-187N(-8)	–	YC-271	–	–	–		–	LFO-41(T)-187N	–	–
SFO-61(T)-250A	–	YC-270	–	–	–		–	LFO-61(T)-250A	–	–
SFPS-61T-250	–	YC-272	–	–	–		–	LFPS-61(T)-250	–	–
SFT-61T-250N	–	YC-510	–	–	–		–	LFT-61T-250N	–	–
SGF-41(T)-4	–	YC-055	–	–	–		–	LGF-41(T)-4	–	–
SGF-51(T)-5	–	YC-065	–	–	–		–	LGF-51(T)-5 LGF-51(T)-5A	–	–
SGM-51T-5	–	YC-056	–	–	–		–	LGM-51T-5	–	–
SHCM-A03T-P025	YRS-960	–	–	–	–		WC-SHCM-A03	–	–	–
SHF-001T-0.8BS	YRS-122	YC-122R	–	–	–		WC-122	BHF-001T-0.8BS	EJ-SMP	–
SHF-002T-0.8BS	YRS-300	–	–	–	–		–	–	EJ-SMP	–
SHIF-01T-P0.5	–	YC-986R	–	–	–		–	–	EJ-HILP	–
SHIF-21T-P0.5	–	YC-995R	–	–	–		–	–	EJ-HILP	–
SHIM-01T-P0.5	–	YC-986R	–	–	–		–	–	EJ-HILR	–
SHIM-21T-P0.5	–	YC-995R	–	–	–		–	–	EJ-HILR	–
SHR-001T-P0.6	YRS-580	YC-580R	–	–	–		–	BHR-001T-P0.6	–	–
SIM-01(T)-110A	–	YC-054	–	–	–		–	LIM-01(T)-110A	–	–
SIM-1.0-250D/N	–	–	–	–	–		JUCS-IM	–	–	–
SIM-2.5-250D/N	–	–	–	–	–		JUCS-IM	–	–	–
SIM-41(T)-110B	–	YC-067	–	–	–		–	LIM-41(T)-110B	–	–
SIM-51(T)-250N	–	YC-321	–	–	–		–	LIM-51(T)-250N	–	–
SIN-001T-1.2	YRS-034	–	–	–	–		–	–	–	–
SIN-002T-1.0S	YRS-035	–	–	–	–		–	–	–	–
SIN-01T-1.2	–	YC-340R	–	–	–		–	LIN-01T-1.2	–	–
SIN-01T-1.8	–	YC-032	–	–	–		–	LIN-01T-1.8	–	–
SIN-01T-1.8N	–	YC-032	–	–	–		–	LIN-01T-1.8N	–	–
SIN-21T-1.8	–	YC-350	–	–	–		–	LIN-21T-1.8	–	–
SIN-21T-1.8S	–	YC-570 YC-571	–	–	–		–	LIN-21T-1.8S	–	–
SIN-61T-2.6S	–	YC-560	–	–	–		–	LIN-61T-2.6S	–	–
SIN-81T-3.6S	–	YC-940	–	–	–		–	LIN-81T-3.6S	–	–

Note: Contact JST for wire range.

Crimping tools

Terminals and parts model number in alphabetical order	Hand tools						Hand tools		Extraction and Insertion tools	
	for chain terminals	for loose piece terminals					for loose piece terminals		Extraction tool	Insertion tool
	YRS series	YC series	YRM series	YRF series	YRK · YRK-EX series		WC & JUC series JUK's Hand Tools	Terminal in loose form model No.		
SJ2F-002GF-P1.0	YRS-8851	–	–	–	YRK-8851		–	–	EJ-JFAJ2N	–
SJ2M-002GF-M1.0N	YRS-8851	–	–	–	YRK-8851		–	–	EJ-JFAJ2N	–
SJ2F-01GF-P1.0	YRS-8861	–	–	–	YRK-8861		–	–	EJ-JFAJ2N	–
SJ2M-01GF-M1.0N	YRS-8861	–	–	–	YRK-8861		–	–	EJ-JFAJ2N	–
SJ2M-01GF-M1.0S	YRS-8861	–	–	–	YRK-8861		–	–	EJ-JFAJ2N	–
SJ2F-21GF-P1.0	–	–	–	YRF-1120	YRK-1120		–	LJ2F-21GF-P1.0	EJ-JFAJ2N	–
SJ2M-21GF-M1.0N	–	–	–	YRF-1120	YRK-1120		–	LJ2M-21GF-M1.0N	EJ-JFAJ2N	–
SJ4F-71GF-M3.0	–	–	–	YRF-1130	–		–	BJ4F-71GF-M3.0	EJ-JFAJ4	–
SJ4F-81GF-M3.0	–	–	–	YRF-1370	–		–	BJ4F-81GF-M3.0	EJ-JFAJ4	–
SJ5F-71GF-M6.5	–	–	–	YRF-888	–		–	LJ5F-71GF-M6.5	EJ-JFAJ5	–
SJ5M-71GF-M6.5	–	–	–	YRF-888	–		–	LJ5M-71GF-M6.5	EJ-JFAJ5	–
SJ5F-81GF-M6.5	–	–	–	YRF-889	–		–	LJ5F-81GF-M6.5	EJ-JFAJ5	–
SJ5M-81GF-M6.5	–	–	–	YRF-889	–		–	LJ5M-81GF-M6.5	EJ-JFAJ5	–
SJ5F-91GF-M6.5	–	–	–	–	–		–	LJ5F-91GF-M6.5	EJ-JFAJ5	–
SJ5M-91GF-M6.5	–	–	–	–	–		–	LJ5M-91GF-M6.5	EJ-JFAJ5	–
SJN-001PT-0.9	YRS-1181	–	–	–	–		–	–	–	–
SJN-002PT-0.9	YRS-036	–	–	–	–		–	–	–	–
SLC-21T-2.0	–	YC-310	–	–	–		WC-310	LLC-21T-2.0	EJ-LC	–
SLC-22T-2.0	–	–	–	–	–		–	–	EJ-LC	–
SLC-001T-P2.0	–	–	–	–	–		–	–	EJ-LCL	–
SLC-02T-P2.0	–	–	–	–	–		–	–	EJ-LCL	–
SLF/M-01T-P1.3E	–	YC-202	YRM-201	–	–		WC-202	LLF/M-01T-P1.3E	LEJ-13	LIT-2013
SLF/M-41T-P1.3E	–	YC-203	–	–	–		WC-203	LLF/M-41T-P1.3E	LEJ-13	–
SMF-01T-1.0	–	YC-081	–	–	–		–	LMF-01T-1.0	–	–
SMF-01T-1.3	–	YC-082	–	–	–		–	LMF-01T-1.3	–	–
SMM-003T-P0.5	YRS-800	–	–	–	–		WC-800	–	–	–
SMR-001T-0.6	YRS-580	YC-580R	–	–			–	BMR-001T-0.6	–	–
SOM-21(T)-187	–	YC-680	–	–			–	LOM-21(T)-187	–	–
SOM-51(T)-250	–	YC-066	–	–	–		WC-066	LOM-51(T)-250	–	–
SOTZP-002GD-P0.18	–	–	–	–	–		–	–	EJ-OTZS	–
SPA-001T-P0.5	–	YC-610R YC-611R	–	–	–		–	BPA-001T-P0.5	EJ-PH	–
SPAL-001T-P0.5	–	YC-610R YC-611R	–	–	–		–	BPAL-001T-P0.5	EJ-PAL	–
SPAL-002T-P0.5	YRS-1340	–	–	–	–		–	–	EJ-PAL	
SPB-1.0-250N-S	–	–	–	–	–		JUCS-PB	–	–	–
SPB-2.5-250N-S	–	–	–	–	–		JUCS-PB	–	–	–
SPF-01T-2.5C	–	YC-043R	–	–	–		–	LPF-01T-2.5C	–	–
SPH-001T-P0.5L	YRS-245	–	–	–	–		–	–	–	–
SPH-002T-P0.5L	YRS-241	–	–	–	–		–	–	EJ-PH	–
SPH-002T-P0.5S	YRS-240	–	YRM-240		–		WC-240	BPH-002T-P0.5S	EJ-PH	–
SPH-004T-P0.5S	YRS-243	–	–	–	–		–	–	EJ-PH	–
SPHD-001T-P0.5	–	YC-610R YC-611R	–	–	–		WC-610	BPHD-001T-P0.5	EJ-PHD-RB	–
SPHD-002T-P0.5	YRS-620	–	YRM-620		–		WC-620	BPHD-002T-P0.5	EJ-PHD-RB	–
SPLI-002T-P0.5	YRS-1410	–	–	–	–		–	–	–	–
SPND-001T-C0.5	YRS-1091	–	–	–	–		–	–	EJ-PND	–
SPND-002T-C0.5	YRS-1090	–	–	–	–		–	–	EJ-PND	–

Note: Contact JST for wire range.

Crimping tools

Terminals and parts model number in alphabetical order	Hand tools						Hand tools		Extraction and Insertion tools	
	for chain terminals	for loose piece terminals					for loose piece terminals		Extraction tool	Insertion tool
	YRS series	YC series	YRM series	YRF series	YRK · YRK-EX series		WC & JUC series JUK's Hand Tools	Terminal in loose form model No.		
SPS-01T-110	–	YC-740	–	–	–		WC-740	LPS-01T-110	–	–
SPS-01T-187(-8)	–	YC-730 YC-731	–	–	–		WC-730	LPS-01T-187(-8)	EJ-PS187	–
SPS-21T-205(-5)	–	YC-760	–	–	–		–	LPS-21T-205(-5)	–	–
SPS-21T-250	–	YC-780	–	–	–		WC-780	LPS-21T-250	EJ-PS250	–
SPS-21T-250S	–	YC-780	–	–	–		WC-780	LPS-21T-250S	EJ-PS250	–
SPS-41T-110	–	YC-750 YC-751	–	–	–		WC-750	LPS-41T-110	–	–
SPS-51T-187(-8)	–	YC-710 YC-711	–	–	–		WC-710	LPS-51T-187(-8)	EJ-PS187	–
SPS-51T-205	–	YC-770 YC-771	–	–	–		–	LPS-51T-205	–	–
SPS-61T-250	–	YC-720	–	–	–		WC-720	LPS-61T-250	EJ-PS250	–
SPS-61T-250S	–	YC-721	–	–	–		–	LPS-61T-250S	EJ-PS250	–
SPS-91T-250	–	–	–	YRF-790	–		–	BPS-91T-250	EJ-PS250	–
SPS-91T-250S	–	–	–	YRF-791	–		–	BPS-91T-250S	EJ-PS250	–
SPUD-001T-P0.5	YRS-1320	–	–	–	–		–	–	EJ-PUD	–
SPUD-002T-P0.5	–	–	–	–	–		–	–	EJ-PUD	–
SPXA-001T-P0.6	–	–	–	–	–		–	–	EJ-PXA	–
SRA-20(T)-**	–	YC-181	–	–	–		–	LRA-20(T)-**	–	–
SRA-21(T)-**	–	YC-141	–	–	–		–	LRA-21(T)-**	–	–
SRA-50(T)-**	–	YC-182	–	–	–		–	LRA-50(T)-**	–	–
SRA-51(T)-**	–	YC-142	–	–	–		–	LRA-51(T)-**	–	–
SRB-1.0-( )	–	–	–	–	–		JUCS-RB/RT	–	–	–
SRB-2.5-( )	–	–	–	–	–		JUCS-RB/RT	–	–	–
SRB-51(T)-**	–	YC-142	–	–	–		–	LRB-51(T)-**	–	–
SRC-01(T)-**	–	YC-033	–	–	–		–	LRC-01(T)-**	–	–
SRC-50(T)-**	–	YC-183	–	–	–		–	LRC-50(T)-**	–	–
SRC-51(T)-**	–	YC-142	–	–	–		–	LRC-51(T)-**	–	–
SRF-51(T)-**	–	YC-142	–	–	–		–	LRF-51(T)-**	–	–
SRT-1.0-( )	–	–	–	–	–		JUCS-RB/RT	–	–	–
SRT-2.5-( )	–	–	–	–	–		JUCS-RB/RT	–	–	–
SRT-51T-**	–	YC-143R	–	–	–		–	LRT-51T-**	–	–
SRWF-01GG-M0.6	–	–	–	–	–		–	–	EJ-RPZ	–
SRWM-01GG-S0.6	–	–	–	–	–		–	–	EJ-RPZ	–
SRWF-21GG-M0.6	–	–	–	–	–		–	–	EJ-RPZ	–
SRWM-21GG-S0.6	–	–	–	–	–		–	–	EJ-RPZ	–
SRWF-61GG-M0.6	–	YC-840R	–	–	–		–	BRWF-61GG-M0.6	EJ-RPZ	–
SRWM-61GG-S0.6	–	YC-840R	–	–	–		–	BRWM-61GG-S0.6	EJ-RPZ	–
SSFH-001T-P0.5	–	–	–	–	–		–	–	EJ-SFH	–
SSFH-002T-P0.5	–	–	–	–	–		–	–	EJ-SFH	–
SSH-003T-P0.2-H	YRS-859	–	–	–	–		WC-SH2832	–	–	–
SSH-003GA-P0.2	YRS-859	–	–	–	–		WC-SH2832	–	–	–
SSHL-002T-P0.2	YRS-1140	–	–	–	–		WC-GH2630	–	–	–
SSHL-003T-P0.2	YRS-859	–	–	–	–		WC-SH2832	–	–	–
SSHL-003GA1-P0.2	YRS-859	–	–	–	–		WC-SH2832	–	–	–
SSF/M-01T-P1.4	–	YC-500	–	–	–		–	BSF/M-01T-P1.4	SLJ-1.4	ITBL-08V
SSF/M-21T-P1.4	–	YC-550	–	–	–		WC-550	BSF/M-21T-P1.4	SLJ-1.4	–
STI-01(T)-110N	–	YC-041	–	–	–		–	LTI-01(T)-110N	–	–

Note: Contact JST for wire range.

Crimping tools

Terminals and parts model number in alphabetical order	Hand tools						Hand tools		Extraction and Insertion tools	
	for chain terminals	for loose piece terminals					for loose piece terminals		Extraction tool	Insertion tool
	YRS series	YC series	YRM series	YRF series	YRK · YRK-EX series		WC & JUC series JUK's Hand Tools	Terminal in loose form model No.		
STI-1.0-250D/N	–	–	–	–	–		JUCS-TI	–	–	–
STI-2.5-250D/N	–	–	–	–	–		JUCS-TI	–	–	–
STI-41(T)-110N	–	YC-063	–	–	–		–	LTI-41(T)-110N	–	–
STI-51(T)-250N	–	YC-322	–	–	–		–	LTI-51(T)-250N	–	–
STO-01(T)-110N(-8)	–	YC-041	–	–	–		–	LTO-01(T)-110N(-8)	–	–
STO-01(T)-187N(-8)	–	YC-042	–	–	–		–	LTO-01(T)-187N(-8)	–	–
STO-0.25-110N	–	YC-810	–	–	–		–	–	–	–
STO-0.5-110N	–	YC-820	–	–	–		JUCS-05110	–	–	–
STO-1.0-110N	–	–	–	–	–		JUCS-2.8/4.8	–	–	–
STO-1.0-187N	–	–	–	–	–		JUCS-2.8/4.8	–	–	–
STO-1.0-250N	–	–	–	–	–		JUCS-6.3	–	–	–
STO-2.5-250N	–	–	–	–	–		JUCS-6.3	–	–	–
STO-21(T)-205N	–	YC-053	–	–	–		–	LTO-21(T)-205N	–	–
STO-21(T)-250N	–	YC-102	–	–	–		–	LTO-21(T)-250N	–	–
STO-41(T)-110N(-8)	–	YC-062	–	–	–		–	LTO-41(T)-110N(-8)	–	–
STO-41(T)-187N(-8)	–	YC-051	–	–	–		–	LTO-41(T)-187N(-8)	–	–
STO-41T-187S	–	YC-064	–	–	–		–	LTO-41T-187S	EJ-187S	–
STO-61(T)-250N	–	YC-047	–	–	–		–	LTO-61(T)-250N	–	–
STO-81(T)-250N	–	YC-280	–	YRF-280	–		–	LTO-81(T)-250N	–	–
STS/D-002GG-P0.6	YRS-1360	–	–	–	–		–	–	EJ-TSD	–
SVA-41T-P1.1	–	YC-450	–	–	–		–	BVA-41T-P1.1	–	–
SVF-01T-1.5A	–	YC-044	–	–	–		–	LVF-01T-1.5A	–	–
SVF-01T-1.5N	–	YC-151	–	–	–		–	LVF-01T-1.5N	EJ-SV	–
SVF-01T-2.36N	–	YC-152	–	–	–		–	LVF-01T-2.36N	EJ-LV	–
SVF-42T-P2.0	–	YC-592	–	–	–		WC-592	BVF-42T-P2.0	VLJ-20	–
SVM-42T-P2.0	–	YC-593	–	–	–		WC-592	BVM-42T-P2.0	VLJ-20	–
SVF/M-61T-P2.0	–	YC-590	–	YRF-590	–		WC-590	BVF/M-61T-P2.0	VLJ-20	–
SVF/M-81T-P2.0	–	–	–	YRF-591	–		WC-591	BVF/M-81T-P2.0	VLJ-20	–
SVH-21T-P1.1	–	YC-160R YC-161R YC-164R	YRM-160 – YRM-164	–	–		WC-160	BVH-21T-(P)1.1	EJ-NV	–
SVH-41T-P1.1	–	YC-930R YC-931R	–	–	–		WC-930	BVH-41T-P1.1	EJ-NV	–
SVT-41T-P1.1	–	YC-630	–	–	–		–	BVT-41T-P1.1	EJ-VT	–
SVU-21T-P0.6	–	YC-990R	–	–	–		–	BVU-21T-P0.6	EJ-VU4	–
SVYF-61T-P0.5A	–	–	–	YRF-536	–		–	–	–	–
SWPJT-21T-P0.5	–	–	–	–	–		–	–	EJ-WPJ	–
SWPJT-21T-P0.5A	–	–	–	–	–		–	–	EJ-WPJ	–
SWPJR-21T-M0.5	–	–	–	–	–		–	–	EJ-WPJ	–
SWPKP-21T-0.6	–	–	–	YRF-1051	–		–	BWPKP-21T-0.6	–	–
SWPKR-21T-0.6	–	–	–	YRF-1050	–		–	BWPKR-21T-0.6	–	–
SWPR-001T-P025	YRS-980	–	–	–	–		WC-JWPF	–	EJ-JWPF	–
SWPT-001T-P025	YRS-980	–	–	–	–		WC-JWPF	–	EJ-JWPF	–
SXA-01T-P0.6	YRS-701	YC-701R	–	–	–		WC-700M	BXA-01T-P0.6	EJ-XAG,EJ-XMP	–
SXA-001T-P0.6	YRS-692	YC-692R	–	–	–		–	BXA-001T-P0.6	EJ-XMP, EJ-XMR	IT-XA
SXA-001T-P0.6L	YRS-691	–	–	–	–		WC-691	–	–	–

Note: Contact JST for wire range.

Crimping tools

Terminals and parts model number in alphabetical order	Hand tools						Hand tools		Extraction and Insertion tools	
	for chain terminals	for loose piece terminals					for loose piece terminals			
	YRS series	YC series	YRM series	YRF series	YRK · YRK-EX series		WC & JUC series JUK's Hand Tools	Terminal in loose form model No.	Extraction tool	Insertion tool
SXAM-01T-P0.6	YRS-701	YC-701R	–	–	–		WC-700M	BXAM-01T-P0.6	EJ-XAW	–
SXAM-001T-P0.6	YRS-692	YC-692R	–	–	–		–	BXAM-001T-P0.6	EJ-XAW	–
SXF-01T-P0.7	–	YC-251	–	–	–		–	BXF-01T-(P)0.7	LEJ-7	–
SXF-41T-P0.7	–	YC-252	–	–	–		–	BXF-41T-(P)0.7	LEJ-7	–
SXH-001T-P0.6	YRS-110	YC-110R YC-111R	–	–	–		WC-110	BXH-001T-P0.6	XJ-06	–
SXH-001T-P0.6N	–	–	–	–	–		–	–	XJ-06	–
SXH-002T-P0.6	YRS-480	–	–	–	–		–	–	XJ-06	–
SXM-01T-P0.6	YRS-701	YC-701R	–	–	–		–	BXM-01T-P0.6	EJ-XAG,EJ-XMP	–
SXM-001T-P0.6	YRS-692	YC-692R	–	–	–		–	BXM-001T-P0.6	EJ-XMP, EJ-XMR	IT-XA
SXNI-001T-P0.6	YRS-1380	–	–	–	–		–	–	–	–
SXNI-003T-P0.6	YRS-1390	–	–	–	–		–	–	–	–
SYF-001T-P0.6	YRS-125	–	–	–	–		–	–	–	–
SYF/M-01T-P0.5A	–	YC-520	–	–	–		WC-520	BYF/M-01T-P0.5A	YLJ-0.5	–
SYF/M-41T-P0.5A	–	YC-530	–	–	–		WC-530	BYF/M-41T-P0.5A	YLJ-0.5	–
SYF-61T-P0.5A	–	–	–	YRF-536	–		–	–	–	–
SYM-001T-P0.6	YRS-121	YC-121R	–	–	–		WC-121	BYM-001T-P0.6	SMJ-06	–
SYM-01T-P0.7	–	YC-251	–	–	–		–	BYM-01T-(P)0.7	LEJ-7	–
SYM-41T-P0.7	–	YC-252	–	–	–		–	BYM-41T-(P)0.7	LEJ-7	–
SZE-002T-P0.3	YRS-1300	–	–	–	–		–	–	–	–
SZE-003T-P0.3	YRS-1330	–	–	–	–		–	–	–	–
SZF/M-01T-P0.7	–	YC-390R	–	–	–		–	BZF/M-01T-(P)0.7	ZLJ-07S	–
SZF/M-41T-P0.7	–	YC-380R	–	–	–		–	BZF/M-41T-(P)0.7	ZLJ-07S	–
SZH-002T-P0.5	YRS-491	–	–	–	–		WC-491	–	–	–
SZH-003T-P0.5	YRS-490	–	–	–	–		WC-490	–	–	–
SZN-002T-P0.7K	YRS-541	–	–	–	–		–	–	–	–
SZN-003T-P0.7K	YRS-540	–	–	–	–		–	–	–	–
SZPD-002T-P0.3	YRS-1460	–	–	–	–		–	–	–	–

Note: Contact JST for wire range.

YRK series hand crimping tools suitable for mass-production

- Crimping work, such as setting contacts to hand tools etc., is facilitated by using a strip contact to improve the productivity.
- A light operation enables to terminate the contact correctly, by adopting straight-ahead crimping.
- A structure, that the carrier of contact doesn't fly off, has been adopted to this tool.

Hand Crimping Tools

YRK Standard type

- When exchanging the crimper, the crimping suitable for the wire specification can be conducted.
- Anvil is fixed to tool.



Dimensions: 75(W)×314(L)×25(D)mm
Weight: Approx. 800g (When assembling dies)

Contact and Applicable dies

Series	Nominal	Contact Model No.		Hand crimp tools	Model No. of crimper *1	Applicable wire size		
		Receptacle	Tab			Marking	AWG	Insulation O.D. (mm)
J1000 Type Ⅱ	L	SF1F-21 (*) -P0.6	SF1M-21 (*) -M0.6A	YRK-1210	LA / LB	LA	#22	1.58
						LB	KV0.75	1.90
					LC / LD	LC	#20	1.76
						LD	#18	2.03
J2000	S	SJ2F-002GF-P1.0	SJ2M-002GF-M1.0N	YRK-8851	SA / SB	SA	#28	1.20
						SB	#24	1.43
	M	SJ2F-01GF-P1.0	SJ2M-01GF-M1.0N	YRK-8861	MA / MB	MA	#24	1.43
						MB	#20	1.53 *2
	L	SJ2F-21GF-P1.0	SJ2M-21GF-M1.0N	YRK-1120	LA / LB	LA	#22	1.58
						LB	#20	1.76
J300	S	SF3F-002 (*) -P2.0	—	YRK-8821	SA / SB	SA	#28	1.20
						SB	#24	1.43
					SC / SD	SC	#26	1.30
						SD	#24	1.11
	M	SF3F-01 (*) -P2.0	SF3M-01 (*) -M2.0N	YRK-8811	MA / MB	MA	#24	1.43
						MB	#20	1.76
					MC / MD	MC	#22	1.58
						MD	#20	2.56
	L	SF3F-41 (*) -P2.0	SF3M-41 (*) -M2.0N	YRK-8801	LA / LB	LA	#20	1.76
						LB	#16	2.35
					LC / LD	LC	#18	2.03
						LD	#18	2.83
	2L	SF3F-71 (*) -P2.0	SF3M-71 (*) -M2.0N	YRK-1071	2LA / 2LB	2LA	#16	3.10
						2LB	#14	3.30

Note: 1. J1000 Finish(*): T ..... Tin-plated
GC ... Gold-plated
2. J300 Finish(*): GF… Nickel-undercoated, 0.38μm selective gold-plated
Gl… Nickel-undercoated, 0.76μm selective gold-plated
T ..... Tin-plated
3. The wear of parts is caused by using hand tool repeatedly.
Measure the crimping height daily and conduct periodical inspection of the wearing parts, such as ratchet, pin and so on.


**1... Crimper is either the pair of A and B or the pair of C and D.*
**2... When using wire type UL 2517.*

Dies replacement type hand crimping tools

YRK-EX

- High reliability of crimping is provided by choosing the crimper and anvil suitable for the wire specification.
- The crimping die can be easily exchanged by only insertion and extraction of pin.
- Common handle and crimping dies can be stored in One case and it is easy to carry.

Patent pending





Dimensions: 75(W)×314(L)×25(D)mm
Weight: Approx. 800g (When assembling dies)



Dimensions: 376(W)×295(L)×73(D)mm

Contact and Applicable dies

Series	Nominal	Contact Model No.		Crimper *1				Anvil	Color mark	Common parts
		Receptacle	Tab	Crimper Model No.	Applicable wire size					
					Die mark	AWG	Insulation O.D. (mm)			
J1000 Type Ⅱ	L	SF1F-21(*)-P0.6	SF1M-21(*)-M0.6A	J1LA / B	A	#20	1.76	J1LL	Yellow green	Handle unit Upper pin Lower pin Case
					B	#18	2.03			
				J1LC / D	C	#22	1.58			
					D	KV0.75	1.90			
J2000	S	SJ2F-002GF-P1.0	SJ2M-002GF-M1.0N	J2SA / B	A	#28	1.20	J2SL	White	
					B	#24	1.43			
	M	SJ2F-01GF-P1.0	SJ2M-01GF-M1.0N	J2MA / B	A	#24	1.43	J2ML	Purple	
					B	#20	1.53 *2			
	L	SJ2F-21GF-P1.0	SJ2M-21GF-M1.0N	J2LA / B	A	#22	1.58	J2LL	Orange	
					B	#20	1.76			
J300	S	SF3F-002 (*) -P2.0	—	J3SA / B	A	#28	1.20	J3SL	Yellow	
					B	#24	1.43			
				J3SC / D	C	#26	1.30			
					D	#24	1.11			
	M	SF3F-01 (*) -P2.0	SF3M-01 (*) -M2.0N	J3MA / B	A	#24	1.43	J3ML	Green	
					B	#20	1.76			
				J3MC / D	C	#22	1.58			
					D	#20	2.56			
	L	SF3F-41 (*) -P2.0	SF3M-41 (*) -M2.0N	J3LA / B	A	#20	1.76	J3LL	Red	
					B	#16	2.35			
				J3LC / D	C	#18	2.03			
					D	#18	2.83			
	2L	SF3F-71 (*) -P2.0	SF3M-71 (*) -M2.0N	J32LA / B	A	#16	3.10	J32LL	Blue	
					B	#14	3.30			

Note: 1. J1000 Finish(*): T ..... Tin-plated
GC ... Gold-plated
2. J300 Finish(*): GF… Nickel-undercoated, 0.38μm selective gold-plated
Gl… Nickel-undercoated, 0.76μm selective gold-plated
T ..... Tin-plated
3. The wear of parts is caused by using hand tool repeatedly.
Measure the crimping height daily and conduct periodical inspection of the wearing parts, such as ratchet, pin and so on.

**1... Crimper is either the pair of A and B or the pair of C and D.*
**2... When using wire type UL 2517.*

LifeElectronics
Живое партнерство

ООО «ЛайфЭлектроникс» **“LifeElectronics” LLC**

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 30101810900000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- *Конкурентоспособные цены и скидки постоянным клиентам.*
- *Специальные условия для постоянных клиентов.*
- *Подбор аналогов.*
- *Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.*

- *Приемлемые сроки поставки, возможна ускоренная поставка.*
- *Доставку товара в любую точку России и стран СНГ.*
- *Комплексную поставку.*
- *Работу по проектам и поставку образцов.*
- *Формирование склада под заказчика.*

- *Сертификаты соответствия на поставляемую продукцию (по желанию клиента).*
- *Тестирование поставляемой продукции.*
- *Поставку компонентов, требующих военную и космическую приемку.*
- *Входной контроль качества.*
- *Наличие сертификата ISO.*

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- *Регистрацию проекта у производителя компонентов.*
- *Техническую поддержку проекта.*
- *Защиту от снятия компонента с производства.*
- *Оценку стоимости проекта по компонентам.*
- *Изготовление тестовой платы монтаж и пусконаладочные работы.*

Тел: +7 (812) 336 43 04 (многоканальный)
Email: org@lifeelectronics.ru

www.lifeelectronics.ru