

Quick Reference Guide

Compressive Board-to-Board Connectors

Compressive Board-to-Board(BTB) connectors are the low cost, high reliability and high design flexibility connectors, which are used to provide either power or signal connections between two printed circuit boards (PCBs) or one PCB and the other electrical modules. This product series is used to save cost and space in consumer electronic devices which continue to get smaller, thinner and less expensive.TE Connectivity's(TE) one-piece compressive BTB connector enables connections to a (locally) gold-plated secondary board by compression of the contacts. It is also scalable in a number of positions, height and pitch.

Key Features

- Provides both power and signal connections with a small form factor.
- Use as a connection for stacking applications between PCB and various solutions such as FPC, electrical modules, speakers and motors.
- Provides single row and dual row contact design for different applications.
- Various options for different working heights, pin counts and contact pitch.
- Up to 2.0 Amp current rating for certain P/N.
- Accommodates soldering and pick-and-place using standard equipment.

Applications

- Smart Phone
- Tablet PC
- Ultraportable computers
- Laptop PC
- Mobile Media Player
- Digital Camera
- Video Camera
- Navigation Systems
- Game Console


te.com/products/compressiveBTB

TE connectivity

Key Features

Flat area on housing provides a flat surface for customer SMT assembly line nozzle pick-and-place.


Preloaded contact provides a reliable and stable electrical contact through the compression stroke.




Radius on the contact tips prevents hooking onto customer operator's glove.

Dimple on the contact ensures better electrical contact under all conditions.

Application



Product Offering

Picture	P/N	Type	Working height	Pos	Pitch	Dimensions	Description	Status
	1551246-2	Dual row	0.9	10	0.7	11.25 x 6.25 x 0.85	10p Compressive-BTB H=0.9mm	MP SH
	2199055-2	Dual row	1.2	10	1.25	5.0 x 6.5 x 0.9	10p Compressive-BTB H=1.2mm	MP GD
	2199172-1	Dual row	1.4	4	1.6	4.8 x 5.0 x 1.2	4p Compressive-BTB H=1.4mm	MP GD
	2199170-1	Dual row	1.4	6	1.6	4.8 x 5.0 x 1.2	6p Compressive-BTB H=1.4mm	MP GD
	2199075-2	Dual row	1.65	4	1.6	5.0 x3.18 x1.4	4p Compressive-BTB H=1.65mm	MP GD
	1932771-1	Dual row	1.65	6	1.6	5.0 x4.78 x1.4	6p Compressive-BTB H=1.65mm	MP GD
	2199035-2	Dual row	1.65	10	1.6	5.0 x7.98 x1.4	10p Compressive-BTB H=1.65mm	MP GD
	2199064-2	Dual row	3.15	6	2.0	5.0 x 5.38 x 2.9	6p Compressive-BTB H=3.15mm	MP GD
	2246092-2	Single row	0.7	2	2.0	5.6 x 5.2 x 0.4	2p Compressive-BTB H=0.7mm	MP SH
	1551120-5	Single row	0.7	8	2.0	17.20 x 5.20 x 0.4	8p Compressive-BTB H=0.7mm	MP SH
	1551759-2	Single row	0.8	8	1.1	11.8 x 3.7 x 0.5	8p Compressive-BTB H=0.8mm	MP SH
	1705536-2	Single row	0.9	10	1.5	6.80 x17.15 x 0.3	10p Compressive-BTB H=0.9mm	MP SH

Notes:
MP: Mass production, SH: Shanghai (PRC), GD: Guangdong (PRC). All dimensions in [mm].

Frequently asked questions

1. What is the working height of TE's compressive BTB products?
TE offers 0.7mm to 3.15mm working heights.

2. What is the centerline spacing requirement?
TE offers the centerline space between 0.7mm to 2.0mm.

3. What are the pin counts of TE's compressive BTB products?
TE offers products ranging from 4 to 22 positions.

4. What is the major application of TE compressive BTB connectors?
This product series can be used in smartphones, tablets, ultraportable devices and laptops. PC MP3 & MP4 players, navigation systems and game consoles.

5. Does my application require a specific current rating?
In general the compressive BTB connectors are rated 1.5 amps maximum current rating; however, there are some exceptions. Please refer to the TE product specification for each part number to confirm.

6. Does my application need a minimum or maximum normal force?
Please refer to the notes in TE's customer drawing, as there are detailed descriptions regarding the contact normal force.

FOR MORE INFORMATION

TE Technical Support Center

Austria:	+43 (0) 1-9056-0
Baltic Regions:	+44 (0) 1-382508080
Canada:	+1 (800) 522-6752
China:	+86 (0) 400-820-6015
France:	+33 (0) 1-3420-8686
Germany:	+49 (0) 6151-607-1999
Italy:	+39 (0) 011-401-2111
Latin/S. America:	+54 (0) 11-4733-2200
Mexico:	+52 (0) 55-1106-0800
Netherlands:	+31 (0) 73-6246-999
Nordic:	+46 (0) 8-5072-5000
Spain/Portugal:	+34 (0) 932-910-330
Switzerland:	+41 (0) 71-447-0447
UK:	+44 (0) 800-267666
USA:	+1 (800) 522-6752

For other country number go to te.com/supportcenter

Part numbers in this brochure are RoHS Compliant*, unless marked otherwise.
*as defined www.te.com/leadfree

te.com

© 2014 TE Connectivity Ltd. family of companies. All Rights Reserved.
1-1773729-8 CD 03/2014
TE Connectivity, TE connectivity (logo) and TE (logo) are trademarks. Other logos, product and/or Company names might be trademarks of their respective owners.

While TE has made every reasonable effort to ensure the accuracy of the information in this brochure, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the inf ormation contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this catalog are for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications.

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001
Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:
moschip.ru
moschip.ru_4
moschip.ru_6
moschip.ru_9